
SC2024

Modular thyristor firing board

PRELIMINARY TECHNICAL INFORMATION

HIGHLIGHTS

- Modular system
- Pulse train firing signal
- Wide range of application topologies
- Standard dimensions for 72 mm DIN rail platform
- SC2024HV version for higher voltages (up to 700 V)
- SC2024-60Hz version for 60 Hz mains



non-contractual image

OVERVIEW

SC2024 is a modular thyristor firing board, which its main feature is its versatility, allowing three different regulation options (0-5 V, 0–10 V and 4-20 mA). Designed to fit in standard 72 mm DIN PCB holders.

It can be used by itself in a numerous of single-phase type of converters, or combining multiple boards in order to regulate other multiple-phase converters listed bellow. And can be set to provide a progressive start-up with maximum time of 20 s.

ELECTRICAL CHARACTERISTICS

Symbol	Parameter	Notes / Test conditions	Min	Typ	Max	Units
V_{CC}	Supply voltage			24		V
I_{CC}	Supply current	*Full conduction, 20 Ω load*	60	65	75	mA
V_{in}	Mains voltage	*SC2024*	50		480	V_{RMS}
		SC2024HV	100		700	
F_{in}	Mains frequency	*SC2024/SC2024HV*		50		Hz
		SC2024-60HZ/SC2024HV-60Hz		60		
f_{P_GATE}	Gate pulse frequency			13		kHz
V_P	Sustaining gate pulse open circuit voltage			6		V
I_{trig}	Trigger current	@ 2.5 V		400		mA
V_{f_max}	Maximum firing voltage (pulse train)	30 Ω load		4		V
I_{sc}	Sustaining gate drive short circuit current	1 Ω load		570		mA
t_{sc_rise}	Short circuit gate drive current rise time			1.5		A/µs
V_{t_max}	Maximum input voltage to pulse transformers			700		V_{RMS}


Load connections	
Single phase application circuits	W1C, M2CA, M2CK, B2HZ, B2HK, B2HA, B2C
Three phase application circuits	W3.2C, W3C, B6HA, B6HK, B6C
Six phase application circuits	M6CA, M6CK, M3.2CA, M3.2CK
Optional phase application circuits	W1H, M1C, W3H, M3CA, M3CK

Reserves the right to change limits, test conditions and dimensions given in this data sheet at any time without previous notice.

CONTROL OPTIONS

Symbol	Parameter	Notes / Test conditions	Min	Typ	Max	Units
V_{ref_5}	Reference signal voltage 0 – 5 V	Selectable with configuration jumpers *(see page 3)*	0		5	V
V_{ref_10}	Reference signal voltage 0 – 10 V		0		10	V
I_{ref}	Reference signal current 4 – 20 mA		4		20	mA
BLQ	External blocking	External open contact				


CONTROL & SUPPLY CONNECTORS:



J1 CONNECTOR:

Pin	*Function*
1	External control signal input
2	GND
3	Blocking (2)
4	24 V power supply

(J1:1) - Pin is an external reference input of 0 – 10V, 0 – 5 V or 4 – 20 mA, that can be selected by setting JP5 and JP6 jumpers as shown in page 4.




(J2:"2) - Connecting the **Blocking** pin to **0V**, the board suppress the thyristor firing pulses, and the converter output voltage becomes 0 V. In case that, the function start up ramp has been selected, when the board is unblocked, then starts a progressive start up with a fixed duration.

J2 CONNECTOR:


J2 connector, is the synchronism voltage reference. Consider different connection types following the schemes below.

The synchronism voltage reference is obtained normally by the corresponding thyristors cathodes. The connection schemes for each configuration are specified in the following pages.



J3 AND J4 CONNECTORS:

J1 and **J3** connectors are the thyristors gate outputs. It has been used the nomenclature **G1** as gate 1, **K1** as cathode 1, **G2** as gate 2, and **K2** as cathode 2.



J6 CONNECTOR:

This connector is used for interconnect different boards in the case of a multi-phase application. A flat cable, which must be previously requested by the customer, brings the power supply, blocking and control signals.

Reserves the right to change limits, test conditions and dimensions given in this data sheet at any time without previous notice.

INTERNAL ADJUSTMENTS

Power-on-ramp




The progressive start-up duration can be adjusted with the potentiometer on board RV1 from 0 to 20 seconds.

Master/Slave setting (JP1 and JP2 jumpers)

JP1 and **JP2** jumpers must be placed between the center and right pins in order for the board to work in single-phase or in master mode in a multi-phase application, and between middle and left pin in order to work as slave in multi-phase applications.

Reference signal type setting (JP3 and JP4 jumpers)

JP3 and **JP4** are meant to set the input signal type to be used. I put configuration must be made in the **master board**, this configuration will not have any effect on boards set as slave.

Voltage		*Current*
0-5V	*0-10V*	*4-20 mA*
		

Synchronism input setting:

JP5 jumper must be active when the synchronism voltage is below **230 V_{RMS}** , and disabled when then voltage synchronism is above **230 V_{RMS}** , or **540 V_{RMS}** in the HV version.

Lighting indications:


ON LED, indicates that the board power supply is on.

BLQ LED, indicates the blocking condition.

Reserves the right to change limits, test conditions and dimensions given in this data sheet at any time without previous notice.

DIMENSIONS

PCB	97x72x26 mm
Fixations	Drill holes Ø 4.3 mm
Weight	96 g



All dimensions in mm

ENVIRONMENTAL SPECS	
Protection grade	IP-00
Maximum humidity	50% Rh @ 35ºC / 70% Rh @ 20ºC
Maximum working temperature	55ºC
Pollution grade	III
Supply isolation	4000 V_{RMS} @ 1min

ACCESSORIES

The board is supplied with the following accessories:

- Isolators and fixing screws.
- Plugging connectors.
- Configuration jumpers.



SCCAB21



SCCAB22

Optionally can be request the following accessories:


- Interconnection flat cable for three-phase assemblies (SCCAB22 reference).
- Interconnection flat cable for 2 boards assemblies (SCCAB21 reference).

Reserves the right to change limits, test conditions and dimensions given in this data sheet at any time without previous notice.


CONNECTION SCHEMES

Following you can find the most typical topology scheme connections. Regarding other configurations please contact us.

B6C (THREE PHASE CONTROLLED BRIDGE).




B6C INVERTED PHASE ROTATION CASE.




Note: For half controlled full bridges (as B6HK, B6HA...) all depicted connections remain the same but changing SCR for diodes.


Reserves the right to change limits, test conditions and dimensions given in this data sheet at any time without previous notice.


B2C (SINGLE PHASE CONTROLLED BRIDGE).






B2HZ (SINGLE PHASE SEMICONTROLLED BRIDGE).







Reserves the right to change limits, test conditions and dimensions given in this data sheet at any time without previous notice.


B2HK (SINGLE PHASE SEMICONTROLLED BRIDGE)






W3C (THREE PHASE WYE AC/AC CONVERTER).







Reserves the right to change limits, test conditions and dimensions given in this data sheet at any time without previous notice.


W1C (SINGLE PHASE AC/AC CONVERTER






M6CK (SIX PHASE AC/DC CONVERTER).







Reserves the right to change limits, test conditions and dimensions given in this data sheet at any time without previous notice.


M3.2CK (SIX PHASE STAR AC/DC CONVERTER).





W3C (THREE PHASE DELTA AC/AC CONVERTER).





Reserves the right to change limits, test conditions and dimensions given in this data sheet at any time without previous notice.

Cost Effective Products

SEMICODE ELECTRONICA

Offers to the market a comprehensive range of products from recognized manufacturers at the best price/quality ratio, this products are provided with a basic reference code that allows maintaining the same product reference even if the original device manufacturer is replaced. SEMICODE product reference has to be considered as a generic brand.

Seeking the market needs and trends, we are constantly increasing the product portfolio with new products and suppliers, please ask for the updated information available to our local contacts.

SEMICODE products include semiconductors, passive components and accessories focused in power electronics market.

Datasheet Annotations:

SEMICODE ELECTRONICA annotate datasheets in the top left hard corner of the front page, to indicate product status. The annotations are as follows:
Tentative information: This is the most tentative form of information and represents a very preliminary specification. No actual design work on the product has been started.
Preliminary Information: The product is in design and development. The datasheet represents the product as it is understood but details may change.
Advance Information: The product design is complete and final characterisation for volume production is well in hand.
No Annotation: The product parameters are fixed and the product is available to datasheet specification.

NOTICE: The technical data are to specify components, not to guarantee their properties.No warranty or guarantee expressed or implied is made regarding delivery or performance. The Company reserves the right to alter without prior notice the specification of any product. Information concerning possible methods of use is provided as a guide only and does not constitute any guarantee that such methods of use will be satisfactory in a specific piece of equipment. It is the user's responsibility to fully determine the performance and suitability of any equipment using such information and to ensure that any publication or data used is up to date.

All brand names and product names used in this publication are trademarks, registered trademarks or trade names of their respective owners.

© SEMICODE ELECTRONICA. TECHNICAL DOCUMENTATION – NOT FOR RESALE